




PCFM Agile FM Stereo Audio Modulator

- 35dBmV minimum adjustable output for optimum carrier to noise performance
- Frequency range 88~108MHz (FM Band)
- Agile push-button tuning and digital display for easy frequency selection
- Non-volatile memory for last channel recall in the event of power failure
- Switch-selectable between stereo and monaural operation
- Signal to noise ratio >60dB provides superior sound quality
- Front panel test point for easy RF level system monitoring
- Auxiliary AC outlet for convenience
- UL Approved



Front View



Rear View

Specifications

Output Frequency Range	88~108MHz	POWER OUTPUT	Receptacle	Yes
Tuning	Agile	Dimensions	19" (W) x 3" (D) x 1.75" (H)	
RF Output Level (min)	35dBmV	Weight	3.6 lbs.	
Spurious Output	>65dB			
Audio Input Type	Monaural/Stereo			
AUDIO FREQUENCY				
Response	50~15,000Hz			
Audio Input Connection	600Ω F-Female Unbalanced			
RF Output Connection	75Ω F-Female			
Voltage Input	115VAC			

Ordering Information

PCFM Agile FM Stereo Audio Modulator